

PreSet™ Adjustable Current Switch

Scaled calibration for proof of flow set-point
Split and solid core models to 150A
N.O. 30VAC/DC or 120VAC output
Optional command relay

Patent Pending



DESCRIPTION

PreSet™ allows for matching sensor set-point to the motor nameplate, eliminating the need to calibrate in energized enclosures and reducing installation time. Sensor will detect motor undercurrent conditions such as belt loss, coupling shear, and mechanical failure on fans and pumps.

APPLICATIONS

- Detecting belt loss, coupling shear, and mechanical failure on fans and pumps
- Monitoring status of industrial processes
- Monitoring status of critical motors


FEATURES

Save time and money while eliminating calibration inside energized enclosures

- Preset™ scaled calibration enables set-point adjustment for proof of flow by simply matching dial to motor full load amps (FLA) nameplate
- Safer: Eliminates calibration in energized enclosures, reduces arc flash hazard
- No need to return to calibrate—saves time and money
- Super low turn-on

Maintenance-free—no call backs

- Superior to traditional adjustable CTs and pressure switches
- Industry leading 7 year warranty




Simply set to motor FLA for proof of flow set-point

Patent Pending



SET-POINT OPERATION


Detects Belt Loss/Coupling Shear!




Now you can easily detect when drive belts slip, break, or pump coupling shear. In fact, a typical HVAC motor that loses its load has a reduction of current draw of up to 50%. That's why our sensors are the industry standard for status.



No hazardous guesswork. Multi-turn adjustments are a thing of the past.




Reduce the risk of arc flash because sensor is calibrated to motor FLA nameplate



Save over 1/2 hour per sensor install—based on field productivity tests.

SPLIT CORE C-2320

OPTIONAL RELAY for additional labor savings



L: 2.5" H: 0.57" W: 2.23"
A: 0.75"x 0.75"

- Mount sensor without removing conductor for installation savings
- Clamp on conductor with iris, or use detachable base to screw or DIN mount
- Larger 0.75" aperture accommodates oversize conductors



L: .84" H: .72" W: 2.06"

- Add to 2320 series to get start/stop/status in a single device
- Reduces the number of installed components... saves time and space
- Removable relay facilitates service

SPLIT CORE - MINI C-2220



L: 2.00" H: .75" W: 1.75"
A: .040"x 0.32"

- Mount sensor without removing conductor for installation savings
- Fits in small enclosures
- Clamp on conductor with iris, or screw mount detachable base

SOLID CORE C-1320



L: 2.40" H: 1.04" W: 1.6"
A: 0.52" diameter

- Compact design
- Aperture accommodates spade terminals

SOLID CORE - MINI C-1220



L: 1.91" H: .88" W: 1.31"
A: 0.30" diameter

- Super small—fits anywhere
- Low cost

ORDERING INFORMATION

SPLIT CORE	Min (on)	Max A	N.O. Output*	Trip LED	Power LED
C-2320-L	0.45A	50A	1.0A@30VAC/DC	•	•
C-2320	0.50A	100A	1.0A@30VAC/DC	•	•
C-2320-H	0.50A	150A	1.0A@30VAC/DC	•	•
C-2320HV	0.50A	100A	0.2A@120VAC	•	•
C-2320HV-L	0.45A	50A	0.2A@120VAC	•	•

SPLIT CORE - MINI

C-2220	1.00A	50A	1.0A@30VAC/DC	•
--------	-------	-----	---------------	---

SOLID CORE

C-1320	0.75A	50A	1.0A@30VAC/DC	•
--------	-------	-----	---------------	---

SOLID CORE - MINI

C-1220-L	0.75A	5A	1.0A@30VAC/DC	•
C-1220	0.75A	50A	1.0A@30VAC/DC	•
C-1220HV-L	0.75A	5A	0.2A@120VAC	•
C-1220HV	0.75A	50A	0.2A@120VAC	•

COMMAND RELAY

Contact rating

Coil

CR3-24	N.O. 10A @ 125VAC	24VAC/DC 15mA nom.
CR4-24	N.C. 10A @ 125VAC	24VAC/DC 15mA nom.
CR3-12	N.O. 10A @ 125VAC	9-12VDC 30mA nom.
CR4-12	N.C. 10A @ 125VAC	9-12VDC 30mA nom.

Other coil voltages available—consult factory




Ordering tip: For best resolution, choose the sensor lowest maximum amperage which accommodates your motor (e.g. 0-50A us -L, 50-100A use standard, 100 to 150A use -H)

SPECIFICATIONS

Standard Output Rating	1.0A@30VAC/DC
Line Voltage Output Rating	0.2A@120VAC (-HV ONLY)
Output Type	NO, solid-state FET
Temperature Rating	-15-60 °C
Insulation Class	600V RMS. For use on insulated conductors only! Use minimum 75 °C insulated conductor
Sensor Power	Induced
Frequency Range	50/60Hz

TYPICAL WIRING



Warning: Refer to installation instructions that accompany product and heed all safety instructions. Do not rely on current status LED to indicate presence



7 year limited warranty