SWITCHBOARD INSTRUMENT SELECTOR GUIDE

Model Type	MCS
Case Style	4¼" Metal
Available	
Input Rating	
AC Milliamperes	X
AC Amperes	X
AC Voltage	X
DC Microamperes	X
DC Milliamperes	X
DC Amperes	X
DC Millivolts	X
DC Voltage	X
Frequency	X
AC Watts	X
AC VARS	X
Power Factor	X
AC Synchroscope	X
RPM Indicator	X
Process Indicator	X






MCS Switchboard specifications in accordance with ANSI C39.1

Accuracy: ±1.0% of full scale basic accuracy class.
Specific accuracies:
Expanded Scale Voltmeter - 0.3% of mid-scale.
Power factor meter - ±1% of fiducial value from 40-120% of rated current.
Synchroscope - ±1% of scale length.
Frequency meters - ± .15Hz @45-55Hz and 55-65Hz, ±0.08Hz 58-62Hz, ±1.3Hz @350-450Hz.
Position of use: Vertical (scale)
Full scale deflection angle: 250°, except synchroscope is 360°
Full scale length: MCS - 6.9 inches.
Scale plate: MCS platform type 2 piece scale with graduations on the outer scale; numerals and legends on the inner scale.
Case: All MCS switchboard instruments have drawn steel case with matt black powder coating.
Cover: Front cover has bezel & window made by one piece of flame retardant Polycarbonate molding with black matte finished bezel area.
Mounting studs: 1/4" x 28 thread.
Terminal studs: 10-32 thread.
Operating temperature range: 0 to 40°C (32 to 104°F).
Storage temperature range: -10 to 50°C (14 to 122°F).
Extreme temperature range: -20°C to 65°C (-4 to 149°F).
Dielectric level: 2300VAC for 1 minute between the electrical circuit and mounting studs.
Overload rating: AC & DC Ammeters – 1.2 x continuous, 10 x for 0.5 seconds, repeated 10 times with 1 minute interval.
Ac & DC Voltmeters and frequency meters – 1.2 x continuous
Response time: 3 seconds maximum

Ordering System

Key to MCS Switchboard Numbering System (See Notes)



NOTES:
1. This tabulation is not all inclusive, to be used for defining cat. nos. only
2. For watt & var cat. nos. digits 7-10 & 12-14 designate rating-cal watts-scale & legend information

How to Order - Specify the following:

1. Complete Part Number or Ordering number or;
2. Provide significant portion of catalog number with word description for differences (e.g. "Similar to MCS103111FAFA, except scale 0-100 kilovars"), or;
3. Provide word description including the following information:

Type: MCS
Rating (Input):.....Amperes AC or DC.....
Volts AC or DC.....
Frequency: 60 Hz, 50 Hz, 400 Hz.....Hz
Scale: Min. Value - Max. Value, Zero left,
Zero-center or offset zero
Legend: Specify words and/or symbols exactly
Potential Transformer Ratio: .....to 120 volts
or.....to.....volts
Current Transformer Ratio:.....to 5 amperes
or .....to .....amperes
Circuit: 2-wire/single-phase, 3-wire/3 phase.
3-phase/4-wire.....other
External Devices; phase Shifting transformers, shunts
transducers, etc .....
Other Options:.....
Special features .....

Shipping & Storage Weights

Instrument		MCS Net (lbs)	MCS Net kg	MCS Ship (lbs)	MCS Ship kg
DC-A/V		1.5	.70	2.4	1.1
AC	V	1.7	.79	2.7	1.2
	A	1.8	.84	2.7	1.2
WATT/VAR	1Ø	2.8	1.3	3.6	1.7
	3Ø3W 3Ø4W	3.0	1.4	3.9	1.8
Power Factor		2.0	.95	3.0	1.4
Frequency		1.8	.82	2.7	1.2
Tachometer		1.6	.80	2.7	1.2
Synchroscope		3.9	1.8	4.8	2.2

Approximate Package Size in Inches / Centimeters

All MCS .....6x 6x 11/15x 15 x 28
Shipping .....7x 7 x 13/18 x 18 x33

Specs subject to change without notice

AC Voltmeters





MCS
Metal Case

AC Voltmeters

Rating (Volts)	Scale (Volts)	Part Number	Ordering Number
Self-Contained, 50/60 Hz			
150	0-150	MCS 103 021 PZPZ	1C9962
250	0-250	MCS 103 021 RSRS	1C9963
300	0-300	MCS 103 021 RXRX	1C9964
500	0-500	MCS 103 021 SFSF	1C9965
600	0-600	MCS 103 021 SJSJ	1C9966
Transformer-Rated, 50/60 Hz			
150	0-300	MCS 103 021 PZRX	1C9968
150	0-600	MCS 103 021 PZSJ	1C9969
150	0-750	MCS 103 021 PZSM	1C9970
150	0-3000	MCS 103 021 PZUA	1C9971
150	0-5250	MCS 103 021 PZUL	1C9972
150	0-6000	MCS 103 021 PZUP	1C9973
150	0-9000	MCS 103 021 PZUY	1C9974
150	0-15kV	MCS 103 021 PZWZ	1C9975
150	0-18kV	MCS 103 021 PZXE	1C9976
150	0-45kV	MCS 103 021 PZXU	1C9977
150	0-150kV	MCS 103 021 PZYR	1C9978
250	0-600kV	MCS 103 021 RSSJ	1C9979
Transformer-Rated, 50/60 Hz			
110-130	110-130	MCS 103 071 PNPN	1C9980
Expanded Scale, Transformer Rated, 50/60 HZ			
110-130	#	MCS 103 071 PN++	1C9981
Ground Detector Type - Single-Phase 50/60 Hz			
150	0-150	MCS 103 GDT PZPZ	1D0098
150	#	MCS 103 GDT PZ..++	1D0099
300	0-300	MCS 103 GDT RXRX	1D0100
600	0-600	MCS 103 GDT SJSJ	1D0101

\# Scale per requisition.
++ Order by description. Specify P.T. (Potential Transformer) ratio if used and scale desired.

Specs subject to change without notice

Burden Data - AC Meters

Type	Impedance in Ohms	Dielectric withstand	Overload rating	Volt – ampere	Power Factor
For Potential circuit					
AC Voltmeter	45.5 Kohms @ 120VAC	2300VAC between electronic circuit and case for 1 minute	X1.2 continuous	< 0.8 VA @ 150V	---------
AC Wattmeter or Var meter	For 3 phase 3 wire Wattmeter 316 K ohm @ 110V For 3 Phase 3 wire Var Meter 273.4 Kohm @ 110V	2600VRMS between electronic circuit and case for 1 minute	Voltage X 2 rating for 5 second Voltage x 1.2 continuous	< 4.5VA for Voltage circuit	1.0
AC Power Factor Meter	For 1 phase PF meter 95.2 K ohm @ 110V For 3 phase PF meter 124.9Kohm @ 415V	2600VRMS between electronic circuit and case for 1 minute	Voltage X 2 rating for 5 second Voltage x 1.2 continuous	< 4.5 VA for Voltage circuit	1.0
Frequency Meter	> 1 Mohm	2300VAC between electronic circuit and case for 1 minute	---------	---------	---------
Synchroscope	TBD	TBD	TBD	TBD	TBD
For Current circuit					
AC Ammeter	0.005 ohms @ 10A	2300VAC between electronic circuit and case for 1 minute	X2 continuous, X 10 for 1 second	< 0.5 VA	---------
AC Wattmeter or Var meter	For 3 phase 3 wire Wattmeter 0.1 ohm @ 1A For 3 Phase 3 wire Var Meter 0.1ohm @ 1A	2600VRMS between electronic circuit and case for 1 minute	Current X10 rating for 5 second, Current X 1.2 continuous	< 2 VA for Current circuit	1.0
AC Power Factor Meter	For 3 phase 3 wire Wattmeter 0.1 ohm @ 1A For 3 Phase 3 wire Var Meter 0.1ohm @ 1A	2600VRMS between electronic circuit and case for 1 minute	Current X10 rating for 5 second, Current X 1.2 continuous	< 2 VA for Current circuit	1.0

*Data based on a per-element basis

Burden Data - DC Meters

DC Voltmeters

Rating (Volts)	Sensitivity (Ohms Per Volt)
50mV – 800V	1,000 ohms / volt for left zero and 2,000 ohms / volt for centre zero

Rating (mV)	Calibrated for 2-way Lead Resistance of 0.04 Ohms as standard**	Ohms Terminal Resistance ± 15%
0-50	0.04	12.50 ohm
50-0-50	0.04	25.0 ohm
0-100	0.04	25.0 ohm
100-0-100	0.04	50 ohm

DC Microammeters

Rating (uA)	Ohms Terminal Resistance ± 15%
0-200	10 Kohm
0-400	2.52 Kohm
0-500	2.5 Kohm

DC Milliammeters / Ammeter

Current Rating	Ohms Terminal Resistance ± 15%
0 - 1 mA	500 ohm
0 - 5 mA	7 ohm
0 – 15 mA	3 ohm
0 – 1 A	0.075 ohm